

EA-B11

Call Button with Microphone

Product Datasheet



The ZYCOO Call Button with Microphone is an expansion accessory that integrates a microphone and an illuminated LED button. It supports flexible installation options, supporting both wall-mounted and flush-mounted (compatible with standard 1-Gang electrical boxes).

When connected to designated models of ZYCOO network speakers (such as SC15, SW15), users can press the call button to dial a pre-configured destination number for two-way communication. When there is an incoming call, the LED on the call button will flash, and users can just press the button to answer the call.

Additionally, it can be configured to trigger the speaker to play audio, such as ringtones, alarms, or custom notification audios, to meet the needs of both emergency alerts and routine announcements.

Features

- Built-in microphone for clear voice communication
- Easy-to-install enclosure design
- Press the button to initiate a call or answer an incoming call for two-way communication (when connected to a compatible ZYCOO network speaker)
- Press the button to trigger the speaker to play ringtones, alarms, or custom notification audios (when connected to a compatible ZYCOO network speaker)
- Press the button to trigger the speaker to execute an HTTP URL action (when connected to a compatible ZYCOO network speaker)
- Configure and control via web GUI (when connected to a compatible ZYCOO network speaker)

Applications

- Schools
- Health Care
- Government Agencies
- Financial Institutions
- Shopping Centers
- Office Buildings
- Hotels
- Airports
- Retail Stores
- Warehouses

Specifications

Physical

Casing (Front Panel)	6063 Aluminum Alloy
Mounting	Flush-mounted or Wall-mounted Installation
Weight	276g
Dimensions	4.49" x 2.76" x 1.18" (114mm x 70mm x 30mm)

Environmental

Operating Temperature	-20°C ~ 70°C (-4°F ~ 158°F)
Storage Temperature	-40°C ~ 70°C (-40°F ~ 158°F)
Humidity	10% - 95% RH (non-condensing)